

Flameproof Carbon Monoxide Detector-Transmitter E2658-CO



Features

- Wall mount robust flameproof metal enclosure
- Suitable for ATEX Zones 2 and 22
- Two analog outputs settable to 4-20 mA or 0-10 V
- RS485 Modbus RTU digital interface
- Relay option

Specifications

Calibration	Carbon monoxide CO
Sensor type	Electrochemical
Sampling method	Diffusion
Typical detection range	0...300 ppm 0...1000 ppm
Maximum overload	2000 ppm
Resolution / digital unit	1 ppm
Repeatability	< ± 5 %
Response time T90	< 30 s
Sensor lifetime	> 10 years
Maintenance interval	12 months
Signal update	Every 1 second
Self-diagnostics	Full functionality check at start-up
Warm-up time	≤ 1 min
Power supply	11...30 VDC (default), 24 VAC or 90...265 VAC as options
Power consumption	< 2 VA
Digital interface	RS485, Modbus RTU protocol
Analog outputs	2 × 4-20 mA / 0-10 V, user settable
Output scale width	Recommended: 5-100% of the range; > 10 × resolution in any case
Enclosure	Grey die-cast aluminium, protection class IP66
Dimensions	H80 × W125 × D57 / H80 × W175 × D80 mm
Operating environment	Industrial indoor and outdoor locations
Operating conditions	-20...+50 °C, 0.9...1,1 atm 0...95% RH non condensing Explosion-safe areas Non-aggressive atmosphere
NOTE! We offer technical solutions for extreme humidity, please ask for more information.	
Relay option (ordering code R)	
Output relays	2 × SPST relays (closing contact), 250 VAC / 30 VDC, 5 A max
Default alarm setpoints	RE1 (LOW): set 25; release 20 ppm RE2 (HIGH): set 35; release 28 ppm

Approvals

Enclosure:

ATEX / IECEx

DEMKO 13 ATEX 1327771U

II 2 G Ex c IIC Gb

II 2 D Ex tb IIIC Db IP66

Glands:

ATEX / IECEx

IBExU08ATEX 1063 X Ex II 1D Ex tD A20 IP 6x Ex

II 2G Ex e II IP68

CE conformity

Flameproof to IEC EN 60079-1



Increased safety to IEC EN 60079-7

EMC Emissions to EN 61000-6-3, EN 61326-1


EMC Immunity to EN 61000-6-1, EN 61000-6-2




Dimensions




Connection diagrams




Version without PSU and relays



Version without PSU and with relays



Version with PSU and without relays



Version with PSU and relays

